

Product information

JOB SITE RADIO DAB



BMR104

Approx. Continuous Run Time (1.0Ah)	4.5 hrs
Approx. Continuous Run Time (1.3Ah)	6.5 hrs
Approx. Continuous Run Time (2.0Ah)	10 hrs
Approx. Continuous Run Time (2.6Ah)	14.5 hrs
Approx. Continuous Run Time (3.0Ah)	17 hrs
Frequency Range FM	87.5 - 108 Mhz
Speakers	2x76mmØ (8Ω)
Practical Output (7.2v)	0.5W x 2
Practical Output (9.6v)	1.0W x 2
Practical Output (10.8v)	1.2W x 2
Practical Output (12v)	1.5W x 2
Practical Output (14.4v)	2.2W x 2
Practical Output (18v)	3.5W x 2



- New design: features silver front control panel and newly designed elastomer bumpers.
- Shower proof withstands up to 5 minutes exposure to rain.
- Dual power source: AC or Makita batteries.
- 2 speaker stereo system.
- Flexible FM antenna can be removed and stored inside of the battery cover on the radio.
- Equipped with Micro USB port for software upgrade.
- Digital tuner
- Soft grip carry handle swivels 90 degrees.

Details correct as of: 22-5-2014

Makita reserve the right to change specifications at any time owing to their policy of constant improvement.

Accessories shown are not necessarily supplied.

www.makita.com